



Auxiliary Contacts

Product Description

F4/F8 auxiliary contacts mainly apply to ac circuit with 50Hz frequency, rated voltage up to AC380V, rated current up to 0.95A under AC-15, or rated voltage up to DC220V, rated current up to 1.5A under DC-13, as signal controller and electrical connection. It is used as an auxiliary contact when the main AC contactors don't have enough contacts. These auxiliary contacts have two groups and four groups with top-mounting and lateral-mounting types. They can meet the GB14048.5 and IEC60947-5-1 standard.

Technical Specification

Model No.			Numbers of contact	Max. quantities for each AC contactor		Weight (kg)
				Top-mounting	Lateral-mounting	
F4-11	1	1	2	1PCS(CJX2-09-170) 2PCS(CJX2-185~620) 2PCS(CJX2-F115~F800)	/	0.036
F4-20	2	0	2			0.036
F4-02	0	2	2			0.036
F4-22	2	2	4			0.036
F4-13	1	3	4			0.036
F4-40	4	0	4			0.036
F4-04	0	4	4			0.036
F4-31	3	1	4			0.036
F8-11	1	1	2			0.036
F8-20	2	0	2			0.036

Technical Data	Model No.	F4	F8
Rated Insulation Voltage(V)		690	690
(A)		10	10
Rated controlling capacity		AC-15 360VA ; DC-13 33(W)	
Rated operating current		AC-15 380V 0.95A; DC-13 220V 0.15A	
Maximum operating frequency(times/h)		3600	3600
Mechanical life		10million	
Electrical life		1million	